

FCK-J-18

7mm Connectors, DC~18GHz

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in these kits you can make error-corrected measurements of devices supplied with 7mm connectors from DC to 18 GHz.

Components

| Part Number | Description | Frequency | Impedance | VSWR | Phase Accuracy | Inner Conductor | Outer Conductor | Size |
|-------------|-------------------------|-----------|--------------|--------|----------------------|---------------------------------|------------------------------|-----------------------|
| | | (GHz) | (Ω) | (Max.) | ($^{\circ}$, Max.) | | | (mm) |
| FOJC-18 | 7mm open | DC~18 | 50 | - | ± 1 | Gold plated beryllium copper | Gold plated beryllium copper | - |
| FSJC-18 | 7mm short | | | - | ± 1 | | | - |
| FCT-J-C-18 | 7mm termination | | | 1.048 | - | | | - |
| FW-J1-CK | 7mm torque wrench | | | - | - | Nickel plated tool steel (Head) | Aluminium, anodised (Handle) | 19.1mm (Opening size) |
| FANJC-M* | N male to 7mm adapter | | | 1.06 | - | Gold plated beryllium copper | Passivated stainless steel | - |
| FANJC-F* | N female to 7mm adapter | | | | | | | |
| Storage Box | | - | - | - | - | Wood | 275*200*80 | |

* ** Equal phase adapter

How To Orders

FCK-J-18-6 All the 6 components in one box.

To order a single component, specify the part number in the first column.