

FCK-N-6-2

N Connectors, DC~6GHz, Economic Type

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in these kits you can make error-corrected measurements of devices supplied with N connectors from DC to 6 GHz.

Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size	
		(GHz)	(Ω)	(Max.)	(°, Max.)			(mm)	
FONC-M-6-2	N male open	DC~6	50	-	±1	Without inner conductor	Passivated stainless steel	-	
FONC-F-6-2	N female open					Gold plated beryllium copper		-	
FSNC-M-6-2	N male short			-	±1	Passivated stainless steel		-	
FSNC-F-6-2	N female short					Gold plated beryllium			-
FCT-N-C-M-6-2	N male termination			1.035	-	Gold plated beryllium copper		-	
FCT-N-C-F-6-2	N female termination								-
FW-N1-CK	N torque wrench			1.05	-	Gold plated beryllium copper		Passivated stainless steel	
FANNC-MM-2*	N male to N male adapter								
FANNC-MF-2*	N male to N female adapter								
FANNC-FF-2*	N female to N female adapter			-	-	-		-	Wood

* Equal phase adapter

How To Order

FCK-N-6-2-10 All the 10 components in one box.

FCK-N-6-2-3M Three in one box, including open, short and termination, male, FONC-M-6-2, FSNC-M-6-2, FCT-N-C-M-6-2.

FCK-N-6-2-3F Three in one box, including open, short and termination, female, FONC-F-6-2, FSNC-F-6-2, FCT-N-C-F-6-2.

FCK-N-6-2-6 Six in one box, including FCK-N-6-2-3M and FCK-N-6-2-3F.

To order a single component, specify the npart umber in the first column.