

FPD8-5-1000-50-S

8-Way, 0.005~1GHz

Features:

- * Small Size
- * Low Insertion Loss

Applications:

- * Amplifiers
- * Mixers
- * Antennas
- * Laboratory Test

Electrical

Frequency:	0.005~1GHz
Insertion Loss:	1.6dB max.
VSWR:	1.5 max.
Isolation:	12dB min.
Amplitude Balance:	±0.2dB
Phase Balance:	±5°
Power @SUM Port:	50W as divider 50W as combiner

Mechanical

Size ^{*1} :	164*126*26mm 6.457*4.961*1.024in
Connectors:	SMA Female
Mounting:	4-Φ4.5mm through-hole


[1] Exclude connectors.

How To Order

FPD8-5-1000-50-S

Customization is available upon request.

Outline Drawings



Unit: mm [in]

Tolerance: ±0.5mm [±0.02in]