

## FBC-29000-30000-60-34S

### Ka-Band, 29~30GHz, 60dB, 3W (34dBm)

**Features:**

- \* Low Power Consumption
- \* High Power Threshold Setting
- \* Fully Modular Design
- \* Integrated Structural Design

**Applications:**

- \* Satellite Earth Station
- \* Satellite Communication
- \* Telecommunication

**Electrical**


---

RF Frequency:	29~30GHz
IF Frequency:	950~1950MHz
Output Power (Psat):	3W (34dBm)
Power Consumption:	60W
Gain:	60dB
Gain Flatness:	3dB/500MHz, 4dB/1000MHz max.
Gain Stability:	4dB max.
Attenuation Control:	0~15dB, step 0.1dB
IM3:	-25dBc
Spurious:	-50dBc
Input/Output VSWR:	1.5/1.35
Phase Noise:	-63dBc/Hz@100Hz -73dBc/Hz@1KHz -83dBc/Hz@10KHz -93dBc/Hz@100KHz
External Reference:	10MHz, 0±5dBm
Supply Voltage:	+18~+36VDC
Impedance:	50Ω

**Environmental**


---

Operating Temperature:	-40~+60°C
Operating Humidity:	0~100%

**Mechanical**


---

IF, Ext.ref. input connector:	50Ω N Female/75Ω F Inch Thread Female
Output Waveguide Size:	WR-28 (BJ320)
Flange:	FBM320
Power Supply:	Aviation socket
Weight:	2Kg

[1] Exclude connectors.

**Outline Drawings**

To be done.

Unit: mm [in]

Tolerance: ±0.5mm [±0.02in]

**How To Order**

**FBC-29000-30000-60-34S-X**

X: Input connector type

Connector naming rules:

N - N female

F - F Inch Thread female

Examples:

To order a Block Up Converter (BUC), 29~30GHz, 60dB, 3W (34dBm), N female, specify FBC-29000-30000-60-34S-N.

Customization is available upon request.