

FCK-2-50

2.4mm Connectors, DC~50GHz

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in the kit you can make error-corrected measurements of devices supplied with 2.4mm connectors from DC to 50 GHz.

Components

Part Number	Description	Frequency	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size	
		(GHz)	(Max.)	(°, Max.)			(mm)	
FO2C-M-50	2.4mm male open	DC~50	-	±2.5	Gold plated beryllium copper	Gold plated beryllium copper	-	
FO2C-F-50	2.4mm female open		-	-			-	
FS2C-M-50	2.4mm male short		-	±2.5			-	
FS2C-F-50	2.4mm female short		-	-			-	
FCT-2-C-M-50	2.4mm male termination		1.052	-			-	
FCT-2-C-F-50	2.4mm female termination		-	-			-	
FW-21-CK	2.4mm torque wrench (0.9Nm torque)		-	-	-	Nickel plated tool steel (Head)	Alumina (Handle)	8 (Opening size)
FA22C-MM*	2.4mm male to 2.4mm male adapter		-	-	-	Gold plated beryllium copper	Gold plated beryllium copper	-
FA22C-MF*	2.4mm male to 2.4mm female adapter		1.12	-	-			-
FA22C-FF*	2.4mm female to 2.4mm female adapter		-	-	-			-
Storage Box			-	-	-	Wood		275*200*80

“*” Equal phase adapter

How To Order

FCK-2-50-10 All the 10 components in one box.

FCK-2-50-3M Three in one box, including open, short and termination, male, FO2C-M-50, FS2C-M-50, FCT-2-C-M-50.

FCK-2-50-3F Three in one box, including open, short and termination, female, FO2C-F-50, FS2C-F-50, FCT-2-C-F-50.

FCK-2-50-6 Six in one box, including FCK-2-50-3M and FCK-2-50-3F.

To order a single component, specify the part number in the first column.