

FCK-3-6-2

3.5mm Connectors, DC~6GHz, Economic Type



Features:
* High Precision

Applications:
* Calibration
* Laboratory Test

Description

With the components in these kits you can make error-corrected measurements of devices supplied with 3.5mm connectors from DC to 6 GHz.

Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size		
		(GHz)	(Ω)	(Max.)	($^{\circ}$, Max.)			(mm)		
FO3C-M-6-2	3.5mm male open	DC~6	50	-	± 1	Without inner conductor	Passivated stainless steel	-		
FO3C-F-6-2	3.5mm female open					Gold plated beryllium copper		-		
FS3C-M-6-2	3.5mm male short			-	± 1	Passivated stainless steel		Passivated stainless steel	-	
FS3C-F-6-2	3.5mm female short					Gold plated beryllium copper			-	
FCT-3-C-M-6-2	3.5mm male termination			1.035	-	-		Gold plated beryllium copper	-	
FCT-3-C-F-6-2	3.5mm female termination									-
FW-31-CK	3.5mm torque wrench			-	-	-		Nickel plated tool steel (Head)	Aluminium oxide (Handle)	8.1 (Opening)
FA33C-MM-2*	3.5mm male to 3.5mm male adapter			1.05	-	-		Gold plated beryllium copper	Passivated stainless steel	-
FA33C-MF-2*	3.5mm male to 3.5mm female adapter									-
FA33C-FF-4*	3.5mm female to 3.5mm female adapter									-
Storage Box		-	-	-	-	Wood	275*200*80/ 145*145*60			

* Equal phase adapter

How To Order

FCK-3-6-2-10 All the 10 components in one box.

FCK-3-6-2-3M Three in one box, including open, short and termination, male, FO3C-M-6-2, FS3C-M-6-2, FCT-3-C-M-6-2.

FCK-3-6-2-3F Three in one box, including open, short and termination, female, FO3C-F-6-2, FS3C-F-6-2, FCT-3-C-F-6-2.

FCK-3-6-2-6 Six in one box, including FCK-3-6-2-3M and FCK-3-6-2-3F.

To order a single component, specify the part number in the first column.