

FCK-K-40-1

2.92mm Connectors, DC~40GHz, Precision type

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in these kits you can make error-corrected measurements of devices supplied with 2.92mm connectors from DC to 40 GHz.

Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size		
		(GHz)	(Ω)	(Max.)	($^{\circ}$, Max.)			(mm)		
FOKC-M-40-1	2.92mm male open	DC~40	50	-	± 6	Gold plated beryllium copper	Gold plated beryllium copper	-		
FOKC-F-40-1	2.92mm female open									
FSKC-M-40-1	2.92mm male short			-	± 4.5			-		
FSKC-F-40-1	2.92mm female short									
FCT-K-C-M-40-1	2.92mm male termination			1.08	-			-		
FCT-K-C-F-40-1	2.92mm female termination									
FW-K1-CK	2.92mm torque wrench			-	-			Nickel plated tool steel (Head)	Aluminium, anodised (Handle)	8.1 (Opening size)
FAKCC-MM*	2.92mm male to 2.92mm male adapter			1.15	-			Gold plated beryllium copper	Gold plated beryllium copper	-
FAKCC-MF*	2.92mm male to 2.92mm female									
FAKCC-FF*	2.92mm female to 2.92mm female									
Storage Box		-	-	-	-	Wood	275*200*80/ 145*145*60			

*" Equal phase adapter

How To Order

- FCK-K-40-1-10** All the 10 components in one box.
- FCK-K-40-1-3M** Three in one box, including open, short and termination, male, FOKC-M-40-1, FSKC-M-40-1, FCT-K-C-M-40-1.
- FCK-K-40-1-3F** Three in one box, including open, short and termination, female, FOKC-F-40-1, FSKC-F-40-1, FSKC-F-40-1.
- FCK-K-40-1-6** Six in one box, including FCK-K-40-1-3M and FCK-K-40-1-3F.

To order a single component, specify the part number in the first column.