

# FCK-N-18-1

## N Connectors, DC~18GHz, Precision type

Features:  
\* High Precision

Applications:  
\* Calibration  
\* Laboratory Test



### Description

With the components in these kits you can make error-corrected measurements of devices supplied with N connectors from DC to 18 GHz.

### Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size	
		(GHz)	( $\Omega$ )	(Max.)	( $^{\circ}$ , Max.)			(mm)	
FONC-M-18-1	N male open	DC~18	50	-	$\pm 1$	Gold plated beryllium copper	Passivated stainless steel	-	
FONC-F-18-1	N female open			-				-	
FSNC-M-18-1	N male short			-	$\pm 1$			-	
FSNC-F-18-1	N female short			-				-	
FCT-N-C-M-18-1	N male termination			-	1.048			-	-
FCT-N-C-F-18-1	N female termination			-				-	-
FW-N1-CK	N torque wrench			-	-	-	Nickel plated tool steel (Head)	Aluminium, anodised (Handle)	19.1 (Opening size)
FANNC-MM-1*	N male to N male adapter			-	1.06	-	Gold plated beryllium copper	Passivated stainless steel	-
FANNC-MF-1*	N male to N female adapter			-		-			-
FANNC-FF-1*	N female to N female adapter			-		-			-
Storage Box		-	-	-	-	Wood	275*200*80/ 145*145*60		

\*" Equal phase adapter

### How To Order

**FCK-N-18-1-10** All the 10 components in one box.

**FCK-N-18-1-3M** Three in one box, including open, short and termination, male, FOKC-M-18-1, FSKC-M-18-1, FCT-K-C-M-18-1.

**FCK-N-18-1-3F** Three in one box, including open, short and termination, female, FOKC-F-18-1, FSKC-F-18-1, FCT-K-C-F-18-1.

**FCK-N-18-1-6** Six in one box, including FCK-N-18-1-3M and FCK-N-18-1-3F.

To order a single component, specify the part number in the first column.