

FCK-N-6-3

N Connectors, DC~6GHz, 3-in-1

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in these kits you can make error-corrected measurements of devices supplied with N connectors from DC to 6 GHz.

Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size
		(GHz)	(Ω)	(Max.)	(°, Max.)			(mm)
Opens	N open	DC~6	50	-	± 0.6	Gold plated beryllium copper	Passivated stainless steel	-
Shorts	N short			-	± 0.6			-
Coaxial Terminations	N termination			1.032	-			-
Connect Joint ¹				-	-	Aluminium oxide		
FANNC-MM ²	N male to N male adapter			1.05	-	Gold plated beryllium copper	Passivated stainless steel	-
FANNC-FF ²	N female to N female adapter							-
Storage Box		-	-	-	-	Aluminium	160*130*65	

[1] The Combination connects the Opens, Shorts and Coaxial Terminations

[2] Equal phase adapter

How To Order

FCK-N-6-3-M 3-in-1, male, including open, short and termination.

FCK-N-6-3-F 3-in-1, female, including open, short and termination.

To order a single component, specify the part number in the first column.