

## FCK-N-9-3

N Connectors, DC~9GHz, 3-in-1

Features:  
\* High Precision

Applications:  
\* Calibration  
\* Laboratory Test



### Description

With the components in these kits you can make error-corrected measurements of devices supplied with N connectors from DC to 9 GHz.

### Components

Part Number	Description	Frequency (GHz)	Impedance ( $\Omega$ )	VSWR (Max.)	Phase Accuracy ( $^{\circ}$ , Max.)	Inner Conductor	Outer Conductor	Size		
								(mm)		
Opens	N open	DC~9	50	-	$\pm 0.8$	Gold plated beryllium copper	Passivated stainless steel	-		
				-	$\pm 0.8$			-		
Shorts	N short			-	$\pm 0.8$			-	-	
				-	$\pm 0.8$			-		
Coaxial Terminations	N termination			-	-			1.032	-	-
				-	-			-	-	
Connect Joint1				-	-	-	-	Aluminium oxide	-	
FANNC-MM <sup>2</sup>	N male to N male adapter			1.06	-	-	Gold plated beryllium copper	Passivated stainless steel	-	
FANNC-FF <sup>2</sup>	N female to N female adapter								-	
Storage Box				-	-	-	-	Aluminium	160*130*65	

[1] The Combination connects the Opens, Shorts and Coaxial Terminations

[2] Equal phase adapter

### How To Order

**FCK-N-9-3-M** 3-in-1, male, including open, short and termination.

**FCK-N-9-3-F** 3-in-1, female, including open, short and termination.

To order a single component, specify the part number in the first column.