

FRC8-1000-2500-K5-N

8-Way, 1~2.5GHz, 500W

Features:

- * Small Size
- * Low Insertion Loss
- * High Reliability

Applications:

- * Radar System
- * Communication System
- * Power Amplifier System
- * Test System


Electrical

Frequency:	1~2.5GHz
Insertion Loss:	0.5dB max.
VSWR:	1.4 max.
Amplitude Balance:	±0.3dB max.
Phase Balance:	±4° max.
Impedance:	50Ω
Power @SUM Port:	500W as combiner

Mechanical

Connectors:	N Male
Mounting:	4-M4 depth 4mm through-hole 4-M4 depth 5mm through-hole

Outline Drawings



Unit: mm [in]

Tolerance: ±0.3mm [±0.012in]

How To Order

FRC8-1000-2500-K5-N

Customization is available upon request.