

FRC8-4000-8000-K3-N

8-Way, 4~8GHz, 300W

Features:

- * Small Size
- * Low Insertion Loss
- * High Reliability

Applications:

- * Radar System
- * Communication System
- * Power Amplifier System
- * Test System

Electrical

Frequency:	4~8GHz
Insertion Loss:	0.8dB max.
VSWR:	1.6 max.
Amplitude Balance:	±0.5dB max.
Phase Balance:	±8° max.
Impedance:	50Ω
Power @SUM Port:	300W CW as combiner
Peak Power:	6000W


Mechanical

Size^{*1}: Φ116*22mm
 Φ4.567*0.866in

Connectors: N female

[1] Exclude connectors.

Outline Drawings



Unit: mm [in]

Tolerance: ±0.3mm [±0.012in]

How To Order

FRC8-4000-8000-K3-N

Customization is available upon request.